

Philips Signage Solutions U-Line Display

84" Edge LED Backlight Ultra HD



BDL8470EU

# Captivate your audience

# With an ultra large screen experience

Experience your content like never before thanks to four times the resolution of a conventional display. This ultra large 84" display offers  $3840 \times 2160$  pixels so refined, so lifelike, it's a window to a new world

# **Optimized for public viewing**

- 4K Ultra HD: resolution like you've never seen it before
- Portrait mode operability
- Designed for 24/7 operation
- Maximizing the impact of your message

• Manage and control your network remotely via SmartControl

- Care about you, your business and your audience
- Keep your content up and running with FailOver
- SmartPower for energy saving



# Specifications

# **Picture/Display**

- Diagonal screen size: 84 inch / 213.5 cm
- Panel technology: IPS
- Optimum resolution: 3840 x 2160 @ 60Hz
- Brightness: 500 cd/m<sup>2</sup>
- Contrast ratio (typical): 1400:1
- Dynamic contrast ratio: 500,000:1
- Aspect ratio: 16:9
- Response time (typical): 12 ms • Pixel pitch: 0.4845 x 0.4845 mm
- Display colors: 1073 M
- Viewing angle (H / V): 178 / 178 degree
- Picture enhancement: 3/2 2/2 motion pull down, 3D Combfilter, 3D MA deinterlacing, Dynamic contrast enhancement, Motion compens. deinterlacing, Progressive scan

### Connectivity

- Video input: VGA (Analog D-Sub), DisplayPort (1.2), DVI-D, HDMI (x3), Composite (BNC), Component (BNC)
- Video output: DisplayPort
- · Audio input: 3.5 mm jack
- · Audio output: 3.5mm jack, External speaker connector
- External control: RS232C (in/out) 2.5 mm jack, RJ45
- Other connections: USB

### **Dimensions**

- Set dimensions (W  $\times$  H  $\times$  D):
- 1910.00 x 1102.00 x 77.80 mm
- Bezel width: 22.60 (R/L), 25.60 (T/B) mm
- Product weight: 70 kg
- VESA Mount: 600 x 500 mm, M8

# Convenience

• Placement: Landscape, Portrait

 Network controllable: RS232, HDMI (One Wire), LAN (RI45)

- Signal Loop Through: RS232, DisplayPort
- · Energy saving functions: Smart Power
- Remote control signal: Lockable
- · Ease of installation: Smart Insert
- Other convenience: Carrying handles
- · Screen saving functions: Pixel Shift, Low Brightness

## Power

- Mains power: 100 ~ 240 VAC, 50 ~ 60 Hz
- Consumption (Typical): 400 W
- Standby power consumption: <0.5W</li>

# **Operating conditions**

- Temperature range (operation): 5 ~ 40 °C
- Temperature range (storage): -20 ~ 60 °C
- Relative humidity: 20 ~ 80 %
- MTBF: 50,000 hour(s)
- for remote control, Quick start guide, Remote Control, User manual on CD-ROM, RS232 cable, HDMI cable

## **Miscellaneous**

- German, Italian, Polish, Russian, Spanish, Turkish, Simplified Chinese, Traditional Chinese, Arabic, apanese
- RoHS, GOST, FCC, Class A
- Warranty: 3 year warranty

# • Keyboard control: Hidden, Lockable

# Sound

Built-in speakers: 2 x 10W RMS

### Accessories

• Included accessories: AC Power Cord, Batteries

- On-Screen Display Languages: English, French,
- Regulatory approvals: CE, UL/cUL, CCC, C-Tick,

ULTRA RESOLUTION

🗡 Smart**Power** 📽 Smart**Control** 

# BDL8470EU/00

# Highlights

# **4K Ultra HD Resolution**

See your Signage Solutions like never before thanks to four times the resolution of a conventional Full HD display. 3840 x 2160 pixels provide and image so refined, so lifelike, it's a window to a new world.

# Portrait mounting possible

This display is also able to be safely and reliably mounted in portrait position.

**SmartControl** 



SmartControl software suite lets you remotely control and manage your network of displays via RJ45 and RS232C. Easy identify your displays and fine-tune all display settings including resolution, brightness, contrast, video wall configurations and cloning of your settings over your complete network.

# FailOver



Keeping your content up and running is critical for demanding commercial applications. While it is unlikely you will face a content disaster, FailOver provides 24/7 protection with a revolutionary technology that plays back-up content on screen in the event of a media player failure. FailOver automatically kicks in when the primary input fails. Simply select a primary input connection and a FailOver connection and your ready for instant protection.

## SmartPower



The backlight intensity can be controlled and pre-set by the system to reduce the power consumption by up to 50%, which saves substantially on energy costs.





Issue date 2015-03-13

© 2015 Koninklijke Philips N.V. All Rights reserved.

or their respective owners.

www.philips.com

Version: 1.0.1

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips N.V.

12 NC: 8670 001 22719 EAN: 87 12581 73058 1